

# LumaView LV-F Series LED Flood Light

Knuckle & Slip Fitter Mount | 5000K | Bronze

## Product Highlights

- Tempered glass lens will not yellow over time
- UV-resistant powder coat finish
- Die-cast aluminum housing
- 120-277V universal voltage
- Built-in surge protection
- 0-10V dimming standard

## Ordering Guide

SKU	Wattage	Mount	Voltage	CCT	Finish
LV-F-95W-BRZ	95W	Slip Fitter	120-277V	5000K	Bronze
LV-F-31-54W-BRZ-KM	31-54W	Knuckle	120-277V	5000K	Bronze
LV-F-31-54W-BRZ-SFM	31-54W	Slip Fitter	120-277V	5000K	Bronze

## Specifications

SKU	Lumens	CRI	PF
LV-F-95W-BRZ	12,000 lm	≥70	≥0.9
LV-F-31-54W-BRZ-KM	4,000–7,000 lm	≥70	≥0.9
LV-F-31-54W-BRZ-SFM	4,000–7,000 lm	≥70	≥0.9

## Electrical

120-277V | PF ≥0.9 | THD <20% | -35°F to 104°F

## Construction & Materials

Die-cast aluminum housing. Bronze powder coat. Tempered glass lens.

Product Images



LumaView Lighting | [info@plainviewlighting.com](mailto:info@plainviewlighting.com) | 331-808-3095